

BN / BNH Series



Key features:

- Touch-down terminals with spring-loaded captive screws
- Jumpers available up to 50A model
- Fuse block with or without blown-fuse indicator in neon or LED
- Mounts on 35mm standard DIN rail



UL Recognized
File No. E78117



CSA Certified
File No. LR64803



File No. R9551701
J9551516 (power blocks)
R9650688 (dual-deck blocks)



Specifications

Model	BNH10W	BNH15MW	BNH15LW	BNH30W
Appearance				
Width	0.275" (7mm)	0.315" (8mm)	0.413" (10.5mm)	0.472" (12mm)
Approvals	UL, CSA, TUV	UL, CSA, TUV	UL, CSA, TUV	UL, CSA, TUV
No. of Poles	1	1	1	1
Wire Sizes	22 to 16 AWG	22 to 14 AWG	22 to 14 AWG	18 to 10 AWG
Voltage/Current	600V / 10A	600V / 10A	600V / 15A	600V / 30A
Terminals	Size	M3	M3	M4
	Type	Touch-down	Touch-down	Touch-down
Mounting	35mm DIN rail	35mm DIN rail	35mm DIN rail	35mm DIN rail
Terminal Torque	(N-m)	0.6 - 1.0	0.6 - 1.0	1.4 - 2.0
	(in-lbs.)	5.3 - 8.9	5.3 - 8.9	12.4 - 17.8
End Plate	BNE15W	BNE15W	BNE15W	BNE30W
DIN Rail Stop	BNL-5	BNL-5	BNL-5	BNL-5
Dust Cover	BNC230	BNC230	BNC230	BNC230
Marking Strip	PVC	BNM7	BNM7	BNM7
	Fiberglass	BNM9	BNM9	BNM9
	End clip	BNM3	BNM3	BNM3
Ring Terminal Jumpers	BNJ16	BNJ26W	BNJ46	BNJ56
Fork Terminal Jumpers	BNJ16F	BNJ26FW	BNJ46F	BNJ56F



1. BNDN1000 aluminum DIN rails are available in 1 meter lengths.
2. Marking strips are sold in 1 meter lengths.
3. Most jumpers are provided with 6 poles (except for BNH50W jumper that is 2-poles only).
4. Remove the "H" in the terminal block part number for standard screw type (ex. BNH10W becomes BN10W).




Specifications, continued

Model		BNH50W	BN75W	BN150W	BNDH15W
Appearance					
Width		0.610" (15.5mm)	0.787" (20mm)	1.024" (26mm)	0.315" (8mm)
Approvals		UL, CSA, TUV	UL, CSA, TUV	UL, CSA, TUV	UL, CSA, TUV
No. of Poles		1	1	1	2
Wire Sizes		16 to 6 AWG	16 to 4 AWG	16 to 0 AWG	22 to 14 AWG
Voltage/Current		600V / 50A	600V / 75A	600V / 150A	600V / 10A
Terminals	Size	M5	M6	M8	M3
	Type	Touch-down	Hex bolt	Hex bolt	Touch-down
Mounting		35mm DIN rail	35mm DIN rail	35mm DIN rail	35mm DIN rail, surface
Terminal Torque	(N-m)	2.6 - 3.7	3.9 - 5.4	10 - 13.5	0.6 - 1.0
	(in-lbs.)	23.1 - 32.8	34.6 - 47.9	88.8 - 119.8	5.3 - 8.9
End Plate		BNE50W	BNE75W	BNE150W	BNDE15W
DIN Rail Stop		BNL-5	BNL-6	BNL-6	BNL-8
Dust Cover		BNC320	BNC420	BNC520	BNC230 (top level) BNC240 (bottom Level)
Marking Strip	PVC	BNM7	BNM7	BNM7	BNM7
	Fiberglass	BNM9	BNM9	BNM9	BNM9
	End clip	BNM3	BNM3	BNM3	BNM3
Connecting Rods		—	—	—	BNR1 10.34" (265mm) BNR2 19.69" (500mm)
Connecting Nuts		—	—	—	BNN1 (2 pieces)
Base Mount Brackets		—	—	—	BNDL2
Ring Terminal Jumpers		BNJ62 (2 pole)	—	—	BNJ26
Fork Terminal Jumpers		—	—	—	BNJ26FW



1. BNDN1000 aluminum DIN rails are available in 1 meter lengths.
2. Marking strips are available in 1 meter lengths.
3. Most jumpers are six poles (except for BNJ62 which is 2 poles only).
4. Remove the "H" in the terminal block part number for standard screw type (ex. BNH50W becomes BN50W).

Specifications, continued

Model	BNF10SW	BNF10NW	BNF10DW
Appearance			
Width	0.591" (15mm)	0.591" (15mm)	0.591" (15mm)
Blown Fuse Indicator	None	Neon (100–300VAC)	LED (24V DC)
Approvals	UL, CSA	UL, CSA	UL, CSA
No. of Poles	1	1	1
Wire Sizes	18 to 10 AWG	18 to 10 AWG	18 to 10 AWG
Voltage/Current	600V/10A maximum	600V/10A maximum	600V/10A maximum
Terminals	Size	M4	M4
	Type	Standard screw	Standard screw
Mounting	35mm DIN rail	35mm DIN rail	35mm DIN rail
Terminal Torque	(N-m)	1.4 - 2.0	1.4 - 2.0
	(in-lbs.)	12.4 - 17.8	12.4 - 17.8
End Plate	BNE20	BNE20	BNE20
DIN Rail Stop	BNL-5	BNL-5	BNL-5
Dust Cover	—	—	—
Marking Strip	BNM7	BNM7	BNM7
Applicable Fuse Size	1/4" x 1-1/4" (6.35 x 31.8mm)	1/4" x 1-1/4" (6.35 x 31.8mm)	1/4" x 1-1/4" (6.35 x 31.8mm)

- 1. BNDN1000 aluminum DIN rails are available in 1 meter lengths.
- 2. Fuses not included.

Dimensions

BNH Series

Part No.	Diagrams	
BNH10W BNH15MW	<p>BNH10W</p>	<p>BNH15MW</p>
BNH15LW BNH30W	<p>BNH15LW</p>	<p>BNH30W</p>
BNH50W	<p>BNH50W</p>	

BN Series

Part No.	Diagrams	
BN75W BN150W	<p>BN75W</p>	<p>BN150W</p>

Part No.	Diagrams	
BNF10SW BNF10NW BNW10DW	<p>BNF10SW/BNF10NW/BNF10DW</p>	<p>BND15W</p>